

# Q4WR Quad 4-wire Interface



The Quad 4 wire interface can connect any 4-wire analogue system into the Green-GO digital Ethernet network.

A 4-wire port consists of a pair of 3-pin XLR in and output ports with a Sub-D9 connector for general purpose in and output for contact closures.

This allows separate audio signals to be injected into and extracted from the Green-GO network All ports can be configured individually through the setup menu of the Quad 4 wire.

A 4-wire port can operate in a full user based mode or a general purpose line in/out mode. The Quad 4-wire interface has a large TFT color screen for easy and quick setup and menu navigation. The display will give a quick overview of transmitted and received audio signals and levels. The general purpose in and outputs can be setup to send and receive calls or cues or to activate channels

## Features

- Easily combinable with any other Green-GO Beltpack or Multi-Channel Station (no separate matrix or interface required)
- Connect any 4-wire device, for example a third party 4-wire intercom matrix.
- Get Audio into and out of the Green-GO system, like Program audio or announcements.
- Connect an audio source from anywhere in the world with a Green-GO bridge device.
- Intercom routing data, system setup & preferences are stored in local memory
- Create your own configuration with the free Green-GO Control software

## Technical Data

- Dimensions: 485 x 150 x 45 mm
- Weight: 2,45 kg
- Connections: 2 x 10/100Mbps Neutrik RJ45 EtherCON, 4 x Neutrik XLR3F, 4 x Neutrik XLR3M, 4 x SUB-D9
- Controls: 1 x 2,2" TFT screen
- , 1 x Rotary Encoder
- Power Supply: PoE (802.3af) or optional external 12V DC Power Supply

## Article Reference

GGO- Q4WR